



参考:アメリカン電機株式会社

BN ノズル

型番		寸法(単位: mm)									
黒色	白色	A 内径	B 外径	C	D	E	F	G ネジ外径	H ナット外径	取付穴 寸法	パンチ・ カッターサイズ
BN8S	BN8S-IV	8	17	18	3	15	4	12	19	13	-
BN10S	BN10S-IV	10	19	19	4	15	4	14	21	15	-
BN12S	BN12S-IV	12	21	19	4	15	4	16	23	17	-
BN14S	BN14S-IV	14	28	21	4	17	4	19	30	20	19/
BN16S	BN16S-IV	16	30	21	4	17	4	21	32	22	/16
BN20S	BN20S-IV	20	35	21	4	17	5	26	37	27	25/22
BN26S	BN26S-IV	26	45	24	4	20	6	32	47	33	31/28
BN30S	BN30S-IV	30	55	30	5	25	6	40	57	41	/36
BN35	BN35-IV	35	60	27	7	20	8	45	62	46	/42
BN40S	BN40S-IV	40	64	30	5	25	6	49	67	50	51/
BN50S	BN50S-IV	50	75	30	5	30	6	60	77	61	/54
BN60S	BN60S-IV	60	92	35	5	30	7	74	94	76	/70
BN70S	BN70S-IV	70	106	35	5	30	7	86	108	87	/82
BN80S	BN80S-IV	80	118	35.5	5.5	30	8	96	121	97	/92
BN90S	BN90S-IV	90	128	35.3	5.5	30	8	105	132	108	/104
BN100S	BN100S-IV	100	140	36	6	30	9	114	144	117	-
BN120S	BN120S-IV	120	162	36	6	30	9	136	166	139	-